

Power System Operation Corporation Limited

Western Regional Load Despatch Centre

GRID EVENTS FOR COMPUTATION OF FREQUENCY RESPONSE CHARACTERISTICS

Last updated on : 08.07.2019

| DATE | ANTECEDENT TIME (A) (From WRLDC SCADA) | POST EVENT TIME (B) (From WRLDC SCADA) | Delta f (in Hz) | Delta P (in MW) | Event Description |
|------------|---|---|--------------------|--------------------|--|
| 05.07.2019 | 03:56:10 | 03:56:20 | 0.07 | 1500 | On 05th June 2019, at 03:56:20 hrs C phase jumper of 220 KV Akal- Bhu Line-I snapped and fallen on 220 KV Bus-I at Akal station as reported by Rajasthan SLDC. It led to the tripping of 220 KV Akal-Bhu Line-I & II, 220 KV Akal- Dangri-I and 400/220 KV ICT-I & II at Akal station. The fault clearing time as per PMU was 680 ms and Wind generation loss in Akal station as per SCADA data is 1500 MW. After 2 minutes of incident, 400 KV Akal-Kankani-I & Akal - Ramgarh-II tripped on over voltage as reported and Wind generation loss at Akal station at this second incident was 300 MW as per SCADA data. The FRC has been calculated for the first incident when generation loss was 1500 MW. |
| 19.05.2019 | 10:35:30 | 10:36:30 | 0.20 | 2975 | On dated 19-May-2019 at 10:35 hrs ,all units in operation i.e. unit 1- 4 & 6 of 210 MW each (Unit -5 was already under planned shutdown for annual Maintenance) and Unit 7-10 of 500MW each at Vindhyachal STPS Stage-1, Stage-2 and Stage-3 tripped along with all 400kV Buses and emanating lines connected to VSTPS Stage-1, Stage-2 and Stage-3. As reported by NTPC, incident started due to R-phase bushing failure of generator transformer of Unit-7 and subsequent tripping of other units on impedance protection and turbine over speed. Around 2975 MW of generation loss occurred as per SCADA Data. |

| | | | | | |
|------------|----------|----------|------|------|--|
| 16.05.2019 | 19:10:00 | 19:11:00 | 0.06 | 1337 | On 16th May 2019, at 19:10 hrs smelter load of Vedanta plant that is coming through Sterlite sub-station became nil as reported. The reason of the incident is still not being intimated by SLDC. Also in the incident, SCADA data of Sterlite station was suspected. The net change in power is calculated from remote end data of 400 kV lines connected to Sterilte station and that change is 1337 MW. |
| 12.04.2019 | 23:55:00 | 23:56:10 | 0.10 | 1865 | At 23:55 hrs, 12/04/19 400 KV Teesta III-Kishanganj tripped on R-Y-N Fault. As a result around 1865 MW generation of the entire complex started to flow through 400 KV Rangpo-Kishenganj S/C which tripped on overload (Back –up overcurrent with each phase current of 4000 amps) and resulted in loss of generation of around 1865 MW. |
| 12.04.2019 | 15:25:20 | 15:26:20 | 0.10 | 1500 | At 15:25 hrs Chandrapur-Bhadrawathi-4, Chandrapur-Chandrapur-1 & 2, Chandrapur U#8 & 9, Dhariwal CTU and STU Unit tripped resulting in 1500 MW generation loss. |
| 11.04.2019 | 13:01:00 | 13:02:00 | 0.04 | 1123 | On 11 April 2019, at 13:00 hrs HVDC Talcher-Kolar pole-I got blocked due to emergency switch off signal from Kolar end. Prior to incident flow on bipole was 2000 MW and in post incident flow on Pole-2 was 1000 MW. The net change in flow on bipole satisfied the SPS criteria and due to SPS operation, load loss of 1123 MW took place in southern region and generation loss of 225 MW in eastern region as per SCADA data. The generation relief in aforesaid units was on account of ramp down which took place in span of minutes, so delta P considered in FRC calculation is of load relief quantum in southern region. |

| | | | | | |
|------------|----------|----------|------|------|--|
| 12.03.2019 | 17:03:00 | 17:04:10 | 0.07 | 1170 | On 12-March-2019 at 17:03 Hrs, two running units at Singareni generating 1170 MW tripped due to Bus-Bar protection operation at 400kV Ramadugu substation. |
| 12.03.2019 | 13:02:00 | 13:03:00 | 0.05 | 1219 | On 12-March-2019 at 13:03 Hrs, HVDC talcher-Kolar pole 2 tripped due to DC earth fault . Prior to incident, power flow on bipole was 2000 MW and after tripping of pole-II, power flow on pole-I jumped to 1250 MW. Then after 1.5 minutes flow on pole-I came down to 150 MW. The SPS associated with HVDC Talcher-kolar pole tripping operated at 13:03 Hrs and led to load relief of approx 1219 MW(as per SCADA data) in southern region. The SPS operation in ER region at 13:04:30, led to generation relief of aprox 734 MW (Talcher stg 2 - 641 MW, GMR-147 MW & JITPL-100 MW). The FRC has been calculated for the incident at 13:03 Hrs as frequency change is more than 0.10 Hz. |
| 05.02.2019 | 11:57:10 | 11:58:10 | 0.03 | 869 | On 05th Feb 2019, at 11:57 Hrs load loss of approx. 869 MW occurred in Northern Region as per SCADA data(Delhi-226 MW, Haryana 152 MW, Rajasthan 400 MW, UP 91 MW) . Only Delhi SLDC has reported that load loss occurred due to outage of 220 kV Sarita Vihar-Badarpur D/C and 220 kV Sarita Vihar- |
| 23.01.2019 | 06:37:10 | 06:38:10 | 0.04 | 961 | On 23rd Januray 2019, at 06:37 Hrs 400KV Jhakri-Panchakula 1, 400KV Jhakri-Rampur 1 tripped due to bus bar protection operated at NJPC during charging of 400KV Jhakri-Karcham 1. Consequently, 961 MW generation loss occurred at both Jhakri and Rampur. |

| | | | | | |
|------------|----------|----------|-------|------|--|
| 16.01.2019 | 12:26:00 | 12:27:10 | 0.05 | 1400 | On 16.01.2019 at 12:25hrs, there was a dropper flashover at 220kV GIS Bhadla substation. There was also tripping of 400kV Jodhpur-Bhadla,400kV Merta-Bhadla,400kV Bhadla-Bikaner 1&2. Solar Generation loss around 1400MW as reported by NRLDC. |
| 30.10.2018 | 19:22:20 | 19:23:20 | 0.16 | 2240 | On 30th Oct 2018, at 19:22 Hrs unit # 30,40 and 50 (830 MW each) of CGPL Mundra UMPP tripped due to generator Class-A2 Protection operation. Total generation loss as per SCADA data was 2240 MW. |
| 29.08.2018 | 04:02:10 | 04:03:30 | 0.05 | 1200 | On 29th Aug 2018 at 04:02 Hrs, 400kV Rampur-Nalagarh Ckt-1 Auto Reclosed Successfully and 400kV Rampur-Nalagarh Ckt-2 tripped on B-N fault, consequently the incident led to SPS operation at NJPC and Rampur Hydro stations causing tripping of 2 nos. units in each station, generation loss of 500 MW and 130 MW respectively. Further, at Karcham Wangtoo, Units-2 and 4 went into NLNE mode (No Load Not Excited) causing generation reduction of around 500 MW. Total Generation Loss reported was around 1200 MW. |
| 12.08.2018 | 15:31:00 | 15:31:50 | 0.046 | 852 | 400 KV Rangpo - Binaguri II tripped on B- N phase fault, SPS -I operated and resulted into tripping of all running units of Teesta 3 (Except Unit one Unit) , one unit each of Jorethang, Tashiding, Chujachen and both units of Dikchu. As per NLDC SCADA Data, Generation loss at this point was 852 MW. |
| 07.08.2018 | 14:17:00 | 14:18:00 | 0.04 | 890 | On 07th August 2018 at 14:17Hrs,KSK unit #2 & unit #4 tripped on operation of reverse power relay. Total Generation loss is around 890 MW. |

| | | | | | |
|------------|----------|----------|------|------|---|
| 06.08.2018 | 13:06:20 | 13:06:30 | 0.05 | 1300 | On 06 Aug 18, at 13:06 hrs, all lines emanating from 400 kV Lonikhand and Chakan tripped at 13:06 hrs. Prior to tripping, MSETCL was attending broken insulator in Chakan Bus coupler. As intimated by Maharashtra SLDC about 1300MW load thrown off in Pune. |
|------------|----------|----------|------|------|---|